

SmartD90 Software Upgrade Procedure

This procedure is only valid to upgrade the SmartD90 from V1.2

1. Copy the downloaded “[SP_v1300.zip](#)” file in a USB pen drive under the route: [root://SmartpUpdate/SP_v1300.zip](#) (Keep Upper and Lower case letters as indicated. Otherwise it won't work)
2. Switch Off the SmartD90



3. Attach the USB Pen drive to a free SmartD90 USB port.
4. Switch On the SmartD90 and wait for about 10min.



5. Log into the maintenance web and check version

There is no any indication of the upgrade progress, or indication that the upgrade has finished.


192.168.110.1/maintenance/adm 3

[Refresh](#) **Start**

System ID : f44d306257ee
System ver. : 1.3.0.0 MEU
System : Ready

Service Info

Service : Fun Print
Hotfolder :
Print Size :
Print Mode : Auto
Finishing : Glossy

[Top Menu](#) 

Start Service

Stop Service

Reboot

Shutdown